

MARINE

GOLF

INDUSTRIAL

AUTO

PLICATIONS

SOLAR

DL 127

LiFePO4 11 YEARS OF WARRANTY

Voltage: 12V

• Reserve Capacity: 7Ah

• Energy [Wh]: 84

Active BMS Protection

• Weight: 2 lbs (0.90 kg)

• Length: 5.94 in (151 mm)

• Width: 2.55 in (65 mm)

• Height: 3.74 in (95 mm)

• F2

• Operating Temperature: -20F to +120F

Battery Charger not included



UL 1642 UN 38.3 IEC 62133



Rated at 7 Amp Hours, this 12 Volt lithium battery packs a punch and is our smallest and lightest battery. The 7Ah is ideal for industrial purposes where you need a long lifespan battery that charges quickly, or for outdoor uses like hiking or camping where weight is at a premium. Crafted out of Lithium Iron Phosphate (LiFePO4) technology this is a battery built to last. With a lifespan of 2,000 charge cycles this battery will last up to 4 times longer than your typical SLA battery. 12 V LiFePO4 charger recommended.

200%

TWICE THE POWER OF TRADITIONAL BATTERIES

1/2

HALF THE WEIGHT

5X

CHARGES UP TO 5X FASTER

8X

LASTS 8X LONG

100%

SAFE & RELIABLE





MODEL DL 12 7 VOLTAGE 12V

CAPACITY **7Ah**

BATTERY TYPE Deep Cycle Lithium Iron Phosphate

CYCLE LIFE > 5,000 CYCLE @ 80% DOD

INTELLIGENCE Active BMS Protection

CERTIFICATION UN38 / UL1642 / IEC62133



PRODUCT + PHYSICAL SPECIFICATIONS

BCI Group Size	Туре	Voltage	Cell(s)	Terminal Type ^G	Dimensions ^c Inches (mm)		Weight Lbs. (kg)	
					Length	Width	Height ^F	
	DL 12 7	12		F2	5.94 (151)	2.55 (65)	3.74 (95)	2 (0.90)

ELECTRICAL SPECIFICATIONS

Capacity ^A Minutes				Energy (kWh)	Short Circuit Current (amps)
@ 25 Amps	5-Hr	10-Hr	20-Hr	20-Hr	
-	7	7	7	84	

CHARGING INSTRUCTIONS

Charger Settings					
Recommended Charging Voltage	14.4V				
Maximum Charging Voltage 15 V					
Maximum Charging Current @ Temperature					
> 32F (0C)	10				
14F to 32 F (-10C TO 0C)	N/R				
-4 F to 14 f (-20C to -10C)	N/R				



CHARGING INSTRUCTIONS

10A max, 14.4V recommended, 15V max. Avoid charging below 32F

CHARGER SOLD SEPARATELY

This battery should be charged using a LiFePO4 compatible charger. Dakota Lithium 12V batteries should be charged at 14.4 volts, higher than AGM or lead acid. Lead acid chargers will work, but will only charge the battery to 80% of capacity.

OPERATIONAL DATA

Optimal Operating Temperature	Recommended Storage Temperature
-20°F to 120°F (-6°C to 49°C) At temperatures below 32°F (0°C)	-20F to 120F (-6C to 49C)
Charging Current Reduced	

Electrical Features						
Continuous Discharge Current	10Amps					
Pulse Discharge Current @ 77°F (25°C)	50 Amps for 300 mS					
Communication	N/A					
BMS Protections	Cell balancing, low/high voltage cutoff, short circuit, high temperature					
BMS Functions	Cell Balancing					
Safety Systems	BMS					
Series Connections						
Parallel Connections						
Discharge Voltage Cutoff	9.0V					
Maximum Discharge Voltage	11.0V					
Data Logging						
Other Features						
Environmental Protection						
Shipping Classification						
Case Flame Rating						
CCA						





HALF THE WEIGHT. TWICE THE POWER

All Dakota Lithium batteries are engineered with Lithium Iron Phosphate technology (LiFePO4) providing long lasting performance in the harshest environments. Allowing you to go further, last longer, and play harder.

11 YEAR WARRANTY

Dakota Lithium offers a best in class 11 year pro-rated warranty on all of our batteries.

AMERICAN INNOVATION & USA BASED SUPPORT

SAFETY

Dakota Lithium has engineered the safest lithium battery technology on the market today - a battery that is safer than the one in your cellphone, camera, or laptop. Here are a few examples of how we manage safety here at Dakota Lithium:

SAFETY BATTERY MANAGEMENT SYSTEM (BMS) - Ensures safety and long battery lifespan All Dakota Lithium batteries include an active BMS protection circuit that handles cell balancing, low voltage cutoff, high voltage cutoff, short circuit protection and temperature protection for increased performance and longer life. Safety measures provided by the BMS prevent overheating. All Dakota Lithium batteries have a BMS that can support linking batteries in series or parallel.

LITHIUM IRON PHOSPHATE - LiFePO4 Different Li-ion batteries use different chemistries. Dakota Lithium exclusively engineers our batteries using lithium iron phosphate or LiFePO4 for short. Lithium Iron Phosphate batteries are the safest lithium battery chemistry. Unlike the cell phone battery in your pocket, or the laptop battery on your desk, the structural stability of LiFePO4 results in significantly less heat generation compared to other lithium chemistries.

NO THERMAL RUNAWAY - Dakota Lithium cells do not produce oxygen The main cause of fire or explosion of a lithium ion battery is due to the cells being compromised or ruptured, which causes thermal runaway. Without proper management, thermal runaway may result in fire. Dakota Lithium LiFePO4 is extremely stable and does not produce the oxygen needed to aid thermal runaway and unlike other lithium battery chemistries will not result in a catastrophic meltdown.

100% COBALT FREE - No rare earth elements NCM and other lithium ion chemistries that contain rare earth elements such as Colton or Cobalt produce oxygen and toxic fumes when ruptured, leading to fire. Dakota Lithium does not contain rare earth elements, and does not produce oxygen or is prone to fire.

CERTIFICATIONS - Tested and certified for safety and reliability Dakota Lithium batteries meet U.N. 38.3 standards and built from grade A cells. Dakota Lithium's cells are UL1642 certified and have been tested per IEC62133 standards. UN Manual of Tests and Criteria certified, and meets all US & International regulations for air, ground, marine, and train transport. Dakota Lithium is ISO Certified per 9001:2015 standards, and select models are produced in ISO 14001 certified facilities. IEC62133 certifications and additional laboratory services are available as required by our OEM clients.

INSTALLATION & CARE - Treat your batteries right When proper installation and battery care is followed, your LiFePO4 battery will be safe and reliable for many years. This includes making sure all connections are tight and proper wiring sizes are used, **compatible chargers** and charging components are used, and the batteries are used for purposes that they are designed for.